



Made in EU



MP-MX-3

3-CHANNEL MIXING PREAMP



BT
Receiver



© 2025 Phoenix Professional Audio GmbH | All rights reserved - Pictures can differ - Deviations in design, colors, errors and technical changes reserved.

MP-MX-3



www.phoenix-pa.com



Fig.: Model MP-MX-3, front & rear side, with remote control

MP-MX-3

3-Channel mixing preamp with MP3 player

2 X MIC / 1 X LINE **BT RECEIVER** **LF/HF-EQ** **PHANTOM** **FLUSH / SURFACE MOUNT**

The compact **3-channel mixing preamp MP-MX-3** is equipped with 2 x microphone & 1 x LINE input (mixable), built-in MP3 player (SD card), a USB interface and BT receiver.

The device can be operated by an included IR remote control.

On the front of the MP-MX-3 preamplifier is the USB interface for connection to the PC (laptop), a slot for the SD memory card, a display and the controls (PREV-NEXT, START-STOP, PAUSE and REPEAT buttons).

With the remote control, all functions can be remotely controlled. In addition, you can switch between the existing SD-CARD interface, BT reception and the USB input.

The preamplifier MP-MX-3 is equipped with high-quality XLR mounting sockets (Neutrik), switchable phantom power 18 V for condenser microphones, LOW / HIGH ON-OFF jumpers per mic input and separate LF / HF sound control for each of the three inputs and master section.






Universal application, easy operation and a high overload resistance characterize the compact preamplifier.

Separate sound control ensures precise room equalization and perfect adaptation to room acoustics.

Volume and equalization are controlled by VOL-LINE and LOW / HIGH-EQ on the front of the MP-MX-3.

A mixed operation of the RCA inputs (LINE) and USB / SD ports is possible.



-  MP3 player with USB port / SD card
-  BT receiver for wireless data transfer
-  Suitable for flush-mount and surface-mount
-  Compact & universally applicable
-  Easiest operation



MP-MX-3 - Continued from previous page

Easiest data transfer

Complete freedom of movement:

The built-in playback module with **BT receiver** (including IR remote control) supports all popular Bluetooth-enabled devices and allows you to **wirelessly transfer music or pre-made text from your mobile phone, PC or MP3 player to the MP-MX-3 and play back.**

Inputs for **USB stick and SD memory card** are available.

Fig.: Playback module (with BT receiver, inputs for USB stick + SD card) & remote control




Fig.: Dimensional drawing MP-MX-3

The output of the MP-MX-3 is **transformer balanced** (galvanic isolation) with **select jumper for 0 dB or +6 dB signal setting** and provides **high noise immunity** at +6 dB setting of the output, so that the signal feedback can be done by JY (ST) Y with 2x2x0.6 line.

The device is suitable for **flush and surface installation.**

The MP-MX-3 is ideal e.g. for gymnastics groups who want to play their MP3 files (on the USB stick, an SD card or a direct connection via Bluetooth-enabled devices) in the gym.

Further optimal applications: e.g. in churches, restaurants, multimedia rooms, schools etc.

Another advantage of the MP-MX-3: It has **no mechanical wear parts**, as it is the case e.g. in CD players.

The MP-MX-3 preamplifier conforms to the Electromagnetic Compatibility Directive 89/336/EEC and the Low Voltage Directive 73/23/EEC.

Technical Details	MP-MX-3
Current consumpt. max.	250 mA
Dimensions	approx. W-141 x H-182 x D-50 (mm)
Display	99 titles Display with max. 9:59:59 time indication
EQ	+/- 12 dB
Frequency response	40 Hz - 20,000 Hz
Line inputs	unbalanced 1 x line inputs 0 dB, 0.775 V / 10 kOhm, CINCH
Mic. inputs	balanced 2 x mic inputs (0.5 - 5 mV / 1 kOhm), XLR standard
On board	MP3 player (SD card), USB interface, BT receiver
Outputs	1 x symm. 0 dB or +6 dB
Phantom power	18 V
Power supply	24 VDC, 1A, 24 W
THD	below 0.3%
Weight	approx. 0.5 kg

Further details in the online shop:



[MP-MX-3 >>](#)

Accessories

- MP-MX-3-AP** Lockable surface-mount housing
- MP-MX-3-UP2** Lockable flush-mount housing
- MP-MX-3-UP** Flush-mount housing



Fig.: MP-MX-3 - application example with surface mount housing MP-MX-3-AP (sold separately)



www.phoenix-pa.com • www.phoenix-pa.com/shop

Tel.: +49 (0) 8062 908 49 84 | Fax: +49 (0) 8062 728 37 37 | E-Mail: info@phoenix-pa.com

PHOENIX PROFESSIONAL AUDIO GMBH

Hermann-Oberth-Str. 12
D-83052 Bruckmühl
Germany